



KGP150 GENSET

Generating Set Powered By **Perkins** **STAMFORD**



Image for illustration purposes only

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	120KW _e / 150KVA	132KW _e / 165KVA
1800rpm, 60 Hz / 440V	135KW _e / 169KVA	150KW _e / 188KVA

Genset Specifications

Engine Make & Model	Perkins 1106A-70TAG2
Origin	UK
Alternator Type	Stamford UCI274F
Control Panel	Deap Sea - 6110
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	
Mechanical Governor	
Electrical Stop Solenoid, Energized to Run	

Compact Size

Fuel System	50%	75%	100%
1500rpm, 50 Hz	16.4	24.7	33.4
1800rpm, 60Hz	19.1	29.1	38.2

*Prime Power (l/hr)

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.
Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. $1 \text{ hp} = 1 \text{ kW} \times 1.36$

Engine Technical Data


No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	105
Stroke, mm	135
Displacement, l	7
Compression Ratio	16:1
Starting	12V Electric
Alternators, Amps	12V/85A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	SX460
Protection	IP23
Temperature Rise, °C	125
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
2.70	0.90	1.5	1460	200



KGP150 GENSET

Generating Set Powered By  **Perkins** **STAMFORD**

Performances	1500rpm	1800rpm
Alternator Efficiency	92.3%	92.4%
Engine Power		
Prime Power, KWm(hp)	131(175.7)	147(197.1)
Standby Power, KWm(hp)	144.1(193.2)	164(218.6)
Alternator		
Prime Power, KWe	128	152

Lubrication System	1500rpm	1800rpm
Oil Consumption (l/hr)	0.2% of fuel consumption	0.2% of fuel consumption
Oil Sump Capacity, l	14.9	14.9
Oil System Capacity Include Filters, l	16.5	16.5

Cooling System	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	22.3	25
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	75.7	80.1
Radiator Cooling Air Flow, m³/min (cfm)	282	316.2
Coolant Capacity, l	21	21

Intake & Exhaust System	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	10.7(377)	15(529)
Heat Rejection Exhaust at Standby Power, KW	-	-
Exhaust Gas Temperature at Standby °C	484	407
Max Allowable Back Pressure in Exhaust Line, Kpa	6.0	6.0
Exhaust Gas Flow at Standby Power, m³/min(cfm)	25.5(902)	32.2(1137)

Accessories	
Oil Drain Pump	Anti-Vibration Pads
Stainless Steel Flexible	Battery Disconnect Switch
Standard Silencer	Fuel Tank Base Frame for 8hrs

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load
- Oil pressure, water temperature, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
- **Alternator**
 - Permanent magnet generator (PMG)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional) Genuine - Perkins

Oil filter, full flow	(1)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

