



KGC640 GENSET

Generating Set Powered By



STAMFORD

Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	512KWe / 640KVA	560KWe / 700KVA
1800rpm, 60 Hz / 440V	545KWe / 681KVA	600KWe / 750KVA

Genset Specifications

Engine Make & Model	Cummins VTA28G5
Origin	India
Alternator Type	Stamford HCI544F
Control Panel	Deap Sea - 7310
Circuit Breaker Type	3 Pole MCCB
Water Cooling System	
Electronic Governor	
Emission Compliant	

Fuel System	50%	75%	100%
1500rpm, 50 Hz	73	104	140
1800rpm, 60Hz	-	-	-

*Prime Power (l/hr)

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.
Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data


No. of Cylinders / Alignment	12/40°
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	139.7
Stroke, mm	152.7
Displacement, l	28
Compression Ratio	13.1:1
Starting	24V Electric
Alternators, Amps	24V/35A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440
Protection	IP23
Temperature Rise, °C	125
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
4.13	1.45	2.38	4350	550



KGC640 GENSET

Generating Set Powered By  **STAMFORD**

Performances	1500rpm	1800rpm
Alternator Efficiency	94.9%	94.9%
Engine Power		
Prime Power, KWm(hp)	538(721)	574(770)
Standby Power, KWm(hp)	584(783)	630(875)
Alternator		
Prime Power, KW	488	570

Lubrication System	1500rpm	1800rpm
Oil Consumption (l/hr)	0.03	0.03
Oil Sump Capacity, l	68	
Oil System Capacity Include Filters, l	83	

Cooling System	1500rpm	1800rpm
Heat Radiation from Engine and Alternator, Power KW	94	-
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	380	-
Radiator Cooling Air Flow, m³/s	12.5	-
Coolant Capacity, l	206	

Intake & Exhaust System	1500rpm	1800rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	52.68(1860)	64.56(2280)
Heat Rejection Exhaust at Standby Power, KW	471	508
Exhaust Gas Temperature at Standby °C	507	502
Max Allowable Back Pressure in Exhaust Line, Kpa	10	10
Exhaust Gas Flow at Standby Power, m³/min(cfm)	122.9(4340)	142.71(5040)

Accessories	
Oil Drain Pump	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Oil
Oil (VDS3 15/40)	Genuine Coolant
Coolant 'Ready Mix'	Fuel Tank Base Frame for 8hrs
Standard Silencer	

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR • Oil pressure, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator -Battery Disconnect Switch -Electrical Governor • Alternator <ul style="list-style-type: none"> -Excitation Boost System (EBS) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filters • General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter	(3)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(2)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty One year or 1000 thousand hours whichever elapsed first against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty.
--

