



Image for illustration purposes only

KMGP1250 GENSET

Generating Set Powered By **PERKINS** **STAMFORD LEROY-SOMER™**

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	900KW _e /1125KVA	1000KW _e /1250KVA

Genset Specification

Engine Make & Model	Perkins 4008-30TAG3		
Origin	UK		
Alternator Type	S6L1D-G41/LSA50.2M6		
Control Panel	Deep Sea - 7310 MKII		
Circuit Breaker Type	3 Pole ACB		
Tropical Cooling System			
Digital Electronic Governor			
Turbocharged			
Exceptional Power to Weight Ratio			
Fuel System <small>(prime)</small>	50%	75%	100%
1500rpm, 50 Hz (L/hr)	120	188	244

International Standards

Engine confirm to ISO 9001 2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	8 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	160
Stroke, mm	190
Displacement, l	30.56 l
Compression Ratio	13.6:1
Starting	24V Electric
Alternators, Amps	24V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG/AREP
Voltage Regulator	MX341/D350
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 150/40
Regulation	±1.0% - ±0.25%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	4.7	2.2	2	7550	N/A
Enclosed	8.5	2.4	2.85	11900	NA

For the enclosed type:-
The sound level is around 85 dB(A) @ 3m .
The height to be increased by 12cm for the hook.

KMGP1250 GENSET

Generating Set Powered By  **Perkins**  **STAMFORD**  **LEROY-SOMER™**

Performances	1500rpm
Alternator Efficiency	94.4%
Engine Power	
Prime Power, KWm(hp)	947(1270)
Standby Power, KWm(hp)	1055(1408)
Alternator	
Prime Power, KW	1008

Lubrication System	1500rpm
Oil Consumption (g/kWhr)	0.4%
Oil Sump Capacity, l	153
Oil System Capacity Include Filters, l	-

Cooling System	1500rpm
Heat Radiation from Engine and Alternator, Power KW	74
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	331
Radiator Cooling Air Flow, m³/min (cfm)	1176(41530)
Coolant Capacity, l	140

Intake & Exhaust System	1500rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	96(3390)
Heat Rejection Exhaust at Standby Power, KW	896
Exhaust Gas Temperature at Standby °C	482
Max Allowable Back Pressure in Exhaust Line, Kpa	7.0
Exhaust Gas Flow at Standby Power, m³/min(cfm)	240(8475)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load • Oil pressure, water temperature, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&output • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine -Coolant heater -Oversize batteries -Extra fuel pre-filter water separato • Alternator - 12wire reconnectable stator/terminal arrangement - - Qadrature droop kit - Anti-condensation heater -Air inlet filters • General -Upgrade to modular controller for paralleling -Upgrade to ACB -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filte , full flow	(3)
Fuel filter	(1)
Ai r filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty
One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer s warranty

