



KMGP-945 GENSET

Generating Set Powered By **PERKINS** **STAMFORD LEROY-SOMER**



Image for illustration purposes only

Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz / 416V	660KWe / 850KVA	756KWe / 945KVA

Genset Specifications

Engine Make & Model Perkins 4006-23TAG3A

Origin UK

Alternator Type S6LID-C41/TAL049C

Control Panel Deep Sea - 7310 MKII

Circuit Breaker Type 3 Pole MCCB

Tropical Cooling System

Digital Electronic Governor

Turbocharged

Exceptional Power to Weight Ratio

Fuel System (prime)	50%	75%	100%
1800rpm, 60Hz (L/hr)	96	144	200

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	160
Stroke, mm	190
Displacement, l	22.92l
Compression Ratio	13.6:1
Starting	24V Electric
Alternators, Amps	24V/70A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG/Self Excited
Voltage Regulator	MX341/R150
Protection	IP23
Temperature Rise, °C	Prime 125/40
Regulation	±1.0% - ±0.8%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	4.05	1.70	2.25	6300	N/A
Enclosed	6.52	2.14	2.45	9300	N/A

For the enclosed type:-
The sound level is around 85 dB(A) @ 3m.
The height to be increased by 12cm for the hook.

KMGP-945 GENSET

Generating Set Powered By  **Perkins** **STAMFORD** **LEROY-SOMER**™

Performances 1800rpm	
Alternator Efficiency	94.5%
Engine Power	
Prime Power, KWm(hp)	715(959)
Standby Power, KWm(hp)	795(1066)
Alternator	
Prime Power, KWe	700

Lubrication System 1800rpm	
Oil Consumption (l/hr)	0.25% of fuel consumption
Oil Sump Capacity, l	-
Oil System Capacity Include Filters, l	113.4

Cooling System 1800rpm	
Heat Radiation from Engine and Alternator, Power KW	90
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	330
Radiator Cooling Air Flow, m³/min (cfm)	1140(40258)
Coolant Capacity, l	105

Intake & Exhaust System 1800rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	78(2554)
Heat Rejection Exhaust at Standby Power, KW	759
Exhaust Gas Temperature at Standby °C	500
Max Allowable Back Pressure in Exhaust Line, Kpa	6.0
Exhaust Gas Flow at Standby Power, m³/min(cfm)	209(7380)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
• AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load • Oil pressure, water temperature, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
• Engine -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator • Alternator -12 wire reconnectable stator/terminal arrangement -Upgrade to AVR MX321 -Qadrature droop kit -Anti-condensation heater -Air inlet filters • General -Upgrade to modular controller for paralleling -Upgrade to ACB -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(3)
Fuel filter	(1)
Air filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty.
--

