



KMGP1385 GENSET

Generating Set Powered By **PERKINS** **STAMFORD LEROY-SOMER**



Image for illustration purposes only

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	1000KW _e /1250KVA	1108KW _e /1385KVA

Genset Specifications

Engine Make & Model	Perkins 4012-46TWG2A		
Origin	UK		
Alternator Type	S6L1D-H4I		
Control Panel	Deep Sea - 7310 MKII		
Circuit Breaker Type	3Pole ACB		
Tropical Cooling System			
Digital Electronic Governor			
Turbocharged			
Exceptional Power to Weight Ratio			
Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	143	196	259

International Standards

Engine conform to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.
Alternator conform to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	12 In Line/60°
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	160
Stroke, mm	190
Displacement, l	45.842
Compression Ratio	13.6:1
Starting	24V Electric
Alternators, Amps	24V/40A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 150/40
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	5.05	1.92	2.39	9250	N/A

KMGP1385 GENSET

Generating Set Powered By  **Perkins** **STAMFORD** **LEROY-SOMER**

Performances 1500rpm	
Alternator Efficiency	95%
Engine Power	1055(1414)
Prime Power, KWm(hp)	1166(1563)
Standby Power, KWm(hp)	
Alternator	
Prime Power, KWe	1120

Lubrication System 1500rpm	
Oil Consumption (l/hr)	0.25% of fuel consumption
Oil Sump Capacity, l	159
Oil System Capacity Include Filters, l	177

Cooling System 1500rpm	
Heat Radiation from Engine and Alternator, Power KW	89
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	403
Radiator Cooling Air Flow, m³/min (cfm)	1662(58692)
Coolant Capacity, l	201

Intake & Exhaust System 1500rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	109(3849)
Heat Rejection Exhaust at Standby Power, KW	1009
Exhaust Gas Temperature at Standby °C	422
Max Allowable Back Pressure in Exhaust Line, Kpa	5.0
Exhaust Gas Flow at Standby Power, m³/min(cfm)	235(8298)

Accessories	
Standard silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load • Oil pressure, water temperature, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator • Alternator <ul style="list-style-type: none"> -12 wire reconnectable stator/terminal arrangement -Upgrade to AVR MX321 -Qadrature droop kit -Anti-condensation heater • General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to ACB -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(3)
Fuel filter	(1)
Air filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty
One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

