



KMGC-1820 GENSET

Generating Set Powered By 

STAMFORD LEROY-SOMER™

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1800rpm,60Hz/416-440V	1295KWe/1619KVA	1456KWe/1820KVA

Genset Specification

Engine Make & Model	Cummins KTA50-G9
Origin	India
Alternator Type	S7L1D-C4I
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole ACB
Water Cooling System	
Electronic Governor	

Fuel System (prime) 50% 75% 100%

1800rpm, 60Hz (L/hr)	180	257	330
----------------------	-----	-----	-----

International Standards

Engine confirm to ISO 9001: 2000, ISO 14001, ISO10054, ISO 3046,BS 5514,DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000,VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100,AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	16/60°V
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	158.8
Stroke, mm	158.8
Displacement,l	50
Compression Ratio	13.9:1
Starting	24V Electric
Alternators,Amps	24V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise,°C	Prime 125 /40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	5.68	2	2.81	10200	NA

KMGC-1820 GENSET STAMFORD

Generating Set Powered By

Performances	1800rpm
Alternator Efficiency	95.2%
Engine Power	
Prime Power, KWm(hp)	1349(1809)
Standby Power, KWm(hp)	1605(1252)
Alternator	
Prime Power, KW	1365

Lubrication System	1800rpm
Oil Consumption (l/hr)	0.03
Oil Sump Capacity, l	178
Oil System Capacity Include Filters, l	204

Cooling System	1800rpm
Heat Radiation from Engine and Alternator, Power KW	200
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	460
Radiator Cooling Air Flow, m³/s	28.2
Coolant Capacity, l	414

Intake & Exhaust System	1800rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	124.5(4400)
Heat Rejection Exhaust at Standby Power, KW	1040
Exhaust Gas Temperature at Standby °C	515
Max Allowable Back Pressure in Exhaust Line, Kpa	6.8
Exhaust Gas Flow at Standby Power, m³/min(cfm)	301.5(10650)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR • Oil pressure, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator -Battery Disconnect Switch -Electrical Governor • Alternator -Excitation Boost System (EBS) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filters • General -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter	(2)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(2)

General Information
<p>Documentation</p> <p>Engine instruction book-English Alternator manual- English Wiring diagram</p> <p>Warranty</p> <p>One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty</p>

