



# KMGP1500-1 GENSET

Generating Set Powered By Perkins

STAMFORD LEROY-SOMER™



Image for illustration purposes only

## Output Ratings

Generating Set Model	Prime Power	Standby Power
1500rpm, 50 Hz/400V	1091KWe/1364KVA	1200KWe/1500KVA

## Genset Specifications

<b>Engine Make &amp; Model</b>	Perkins 4012-46TWG3A		
<b>Origin</b>	UK		
<b>Alternator Type</b>	S6L1D-H4I		
<b>Control Panel</b>	Deep Sea - 7310 MKII		
<b>Circuit Breaker Type</b>	3 Pole ACB		
<b>Tropical Cooling System</b>			
<b>Digital Electronic Governor</b>			
<b>Turbocharged</b>			
<b>Exceptional Power to Weight Ratio</b>			
<b>Fuel System (prime)</b>	<b>50%</b>	<b>75%</b>	<b>100%</b>
1500rpm, 50 Hz (L/hr)	151	213	283

## International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



## RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

## Engine Technical Data


<b>No. of Cylinders / Alignment</b>	12 In Line/60°
<b>Cycle</b>	4 Stroke
<b>Aspiration</b>	Turbocharged
<b>Injection</b>	Direct
<b>Bore, mm</b>	160
<b>Stroke, mm</b>	190
<b>Displacement, l</b>	45.842
<b>Compression Ratio</b>	13:1
<b>Starting</b>	24V Electric
<b>Alternators, Amps</b>	24V/40A

## Alternator Technical Data

<b>No. of Bearings</b>	Single Bearing
<b>Insulation System</b>	Class H
<b>Excitation</b>	PMG
<b>Voltage Regulator</b>	MX34I
<b>Protection</b>	IP23
<b>Temperature Rise, °C</b>	Prime 125/40 Standby 163/27
<b>Regulation</b>	±1.0%
<b>No. of Phases</b>	3
<b>No. of Poles</b>	4

## Dimensions & Weights

Length(m)	Width(m)	Height(m)	Weight(kg)	Tank Capacity(L)
5.10	1.85	2.55	9250	N/A



# KMGP1500-1 GENSET

Generating Set Powered By  **Perkins**  **STAMFORD LEROY-SOMER™**

Performances 1500rpm	
<b>Alternator Efficiency</b>	95%
<b>Engine Power</b>	1149(1540)
Prime Power, KWm(hp)	1263(1694)
Standby Power, KWm(hp)	
<b>Alternator</b>	
Prime Power, KW	1120

Lubrication System 1500rpm	
<b>Oil Consumption (l/hr)</b>	0.52% of fuel consumption
<b>Oil Sump Capacity, l</b>	157.5
<b>Oil System Capacity Include Filters, l</b>	177

Cooling System 1500rpm	
<b>Heat Radiation from Engine and Alternator, Power KW</b>	96
<b>Heat Rejection to Coolant and Lube Oil at Standby Power, KW</b>	445
<b>Radiator Cooling Air Flow, m<sup>3</sup>/min (cfm)</b>	1866(65897)
<b>Coolant Capacity, l</b>	201

Intake & Exhaust System 1500rpm	
<b>Air Flow Combustion at Standby Power, m<sup>3</sup>/min(cfm)</b>	115(4061)
<b>Heat Rejection Exhaust at Standby Power, KW</b>	1138
<b>Exhaust Gas Temperature at Standby °C</b>	479
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>	5.0
<b>Exhaust Gas Flow at Standby Power, m<sup>3</sup>/min(cfm)</b>	245(8652)

Accessories	
<b>Standard silencer</b>	<b>Anti-Vibration Pads</b>
<b>Stainless Steel Flexible</b>	<b>Genuine Coolant 'Ready Mix'</b>
<b>Genuine Oil</b>	

Control Panel Readings
<ul style="list-style-type: none"> <li>• AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.</li> <li>• Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load</li> <li>• Oil pressure, water temperature, low oil level, high oil temperature</li> <li>• DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure</li> <li>• Low coolant level - Configurable inputs&amp;outputs</li> <li>• Upgradable for GSM network connection, Signal SMS messages.</li> </ul>

Optional Equipment
<ul style="list-style-type: none"> <li>• <b>Engine</b></li> <li>-Coolant heater</li> <li>-Oversize batteries</li> <li>-Extra fuel pre-filter water separator</li> <li>• <b>Alternator</b></li> <li>-12 wire reconnectable stator/terminal arrangement</li> <li>-Upgrade to AVR MX321</li> <li>-Qadrature droop kit</li> <li>-Anti-condensation heater</li> <li>-Air inlet filters</li> <li>• <b>General</b></li> <li>-Upgrade to modular controller for paralleling</li> <li>-Upgrade to ACB</li> <li>-Battery charger</li> <li>-Automatic transfer switch</li> <li>-Fuel level switch High / Low for alarm and control</li> <li>-Fuel transfer pump Automatic / Manual</li> <li>-Residential grade silencer</li> <li>-Weather protective and acoustic enclosure.</li> </ul>

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(3)
Fuel filter	(1)
Air filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information
<b>Documentation</b> Engine instruction book-English Alternator manual- English Wiring diagram

Warranty
OnOne year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

