



KMGP2000-1 GENSET

Generating Set Powered By Perkins



Image for illustration purposes only

STAMFORD LEROY-SOMER™

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz,400V	1492KWe/1865KVA	1600KWe/2000KVA

Genset Specifications

Engine Make & Model Perkins 4016-61TRGI

Origin UK

Alternator Type S7L1D-F4I

Control Panel Deep Sea - 7310 MKII

Circuit Breaker Type 3 Pole ACB

Tropical Cooling System

Digital Electronic Governor

Turbocharged

Exceptional Power to Weight Ratio

Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	193	280	371

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	16V/60°
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	160
Stroke, mm	190
Displacement, l	61.123
Compression Ratio	13.6:1
Starting	24V Electric
Alternators, Amps	24V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	5.8	2.2	2.5	13100	N/A

KMGP2000-1 GENSET

Generating Set Powered By  **Perkins**  **STAMFORD LEROY-SOMER™**

Performances 1500rpm	
Alternator Efficiency	95.8%
Engine Power	
Prime Power, KWm(hp)	1558(2088)
Standby Power, KWm(hp)	1684(2257)
Alternator	
Prime Power, KW	1520

Lubrication System 1500rpm	
Oil Consumption (g/kWhr)	0.52
Oil Sump Capacity, l	213
Oil System Capacity Include Filters, l	237

Cooling System 1500rpm	
Heat Radiation from Engine and Alternator, Power KW	91
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	471
Radiator Cooling Air Flow, m³/min (cfm)	2160(76279)
Coolant Capacity, l	270

Intake & Exhaust System 1500rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	165(5826)
Heat Rejection Exhaust at Standby Power, KW	1419
Exhaust Gas Temperature at Standby °C	425
Max Allowable Back Pressure in Exhaust Line, Kpa	4.0
Exhaust Gas Flow at Standby Power, m³/min(cfm)	400(14125)

Accessories	
Standard Silencer	Anti-Vibration Pads Genuine
Stainless Steel Flexible	Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load • Oil pressure, water temperature, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator • Alternator -12 wire reconnectable stator/terminal arrangement -Upgrade to AVR MX321 -Qadrature droop kit -Anti-condensation heater -Air inlet filters • General -Upgrade to modular controller for paralleling -Upgrade to ACB -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(3)
Fuel filter	(1)
Air filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty
 One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

