



KMGC-1250-2 GENSET

Generating Set Powered By



STAMFORD

LEROY-SOMER™

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz / 416V	920KWe/1150KVA	1000KWe/1250KVA

Genset Specification

Engine Make & Model	Cummins KTA38-G14		
Origin	India		
Alternator Type	S6L1D-E4		
Control Panel	Deep Sea - 7310 MKII		
Circuit Breaker Type	3Pole ACB		
Water Cooling System			
Electronic Governor			
Fuel System (prime)	50%	75%	100%
1800rpm, 60Hz (L/hr)	136	189	242

International Standards

Engine confirm to ISO 9001: 2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	12/60°V
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	159
Stroke, mm	159
Displacement, l	38.2
Compression Ratio	13.9:1
Starting	24V Electric
Alternators, Amps	24V/35A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	4.55	1.75	2.31	7550	NA

KMGC-1250-2 GENSET

Generating Set Powered By

STAMFORD LEROY-SOMER™

Performances 1800rpm	
Alternator Efficiency	95.2%
Engine Power	
Prime Power, KWm(hp)	971(1302)
Standby Power, KWm(hp)	1065(1428)
Alternator	
Prime Power, KW	920

Lubrication System 1800rpm	
Oil Consumption (l/hr)	-
Oil Sump Capacity, l	114
Oil System Capacity Include Filters, l	135

Cooling System 1800rpm	
Heat Radiation from Engine and Alternator, Power KW	104
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	611
Radiator Cooling Air Flow, m³/s	17.2
Coolant Capacity, l	210

Intake & Exhaust System 1800rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	90.89(3210)
Heat Rejection Exhaust at Standby Power, KW	768
Exhaust Gas Temperature at Standby °C	486
Max Allowable Back Pressure in Exhaust Line, Kpa	10.13
Exhaust Gas Flow at Standby Power, m³/min(cfm)	239(8446)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR • Oil pressure, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator -Battery Disconnect Switch -Electrical Governor • Alternator <ul style="list-style-type: none"> -Excitation Boost System (EBS) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filters • General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter	(2)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(2)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty
 One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

