



KMGC-563 GENSET

Generating Set Powered By



Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1800rpm,60 Hz/416V	400KW _e /500KVA	450KW _e /563KVA

Genset Specifications

Engine Make & Model	Cummins M15-G8
Origin	China
Alternator Type	HCI544C/S4LID-G4I/TAL0473B
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	
Digital Electronic Governor	
Turbocharged	
Exceptional Power to Weight Ratio	

Fuel System (prime)	50%	75%	100%
1800rpm, 60 Hz (L/hr)	52	77	103

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**



Image for illustration purposes only

STAMFORD LEROY-SOMER™

Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	135
Stroke, mm	169
Displacement, l	14.5
Compression Ratio	23:1
Starting	24V Electric
Alternators, Amps	24V/90A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R120
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1.0% - ±0.8
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	3.65	1.37	2.17	3750	370
Enclosed	4.99	1.79	2.35	6200	560

For the enclosed type:-
The sound level is around 85 dB(A) @ 3m .
The height to be increased by 12cm for the hook.

KMGC-563 GENSET

Generating Set Powered By 

Performances	1800rpm
Alternator Efficiency	94.0%
Engine Power	
Prime Power, KWm(hp)	439(588)
Standby Power, KWm(hp)	485(650)
Alternator	
Prime Power, KWe	420

Lubrication System	1800rpm
Oil Consumption (l/hr)	-
Oil Sump Capacity, l	52
Oil System Capacity Include Filters, l	57

Cooling System	1800rpm
Heat Radiation from Engine and Alternator, Power KW	46
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	166
Radiator Cooling Air Flow, m³/s	8.7
Coolant Capacity, l	83.1

Intake & Exhaust System	1800rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	37.2(1317)
Heat Rejection Exhaust at Standby Power, KW	325
Exhaust Gas Temperature at Standby °C	444
Max Allowable Back Pressure in Exhaust Line, Kpa	10
Exhaust Gas Flow at Standby Power, m³/min(cfm)	82.6(2917)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

STAMFORD LEROY-SOMER™

Control Panel Readings
<ul style="list-style-type: none"> • AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. • Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load • Oil pressure, water temperature, low oil level, high oil temperature • DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure • Low coolant level - Configurable inputs&outputs • Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> • Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator • Alternator <ul style="list-style-type: none"> -Permanent magnet generator (PMG) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filters • General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter,	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Coolantfilter	(1)

General Information
Documentation Engine instruction book-English Alternator manual- English Wiring diagram

Warranty One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty.
--

