



KMGC3000 GENSET

Generating Set Powered By



STAMFORD **LEROY-SOMER**

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	2200KWe/2750kVA*	2400KWe/3000kVA*

(*) using electrically driven radiator

Genset Specifications

Engine Make & Model	Cummins QSK78-G9
Origin	UK
Alternator Type	S7LID-K4I
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole ACB
Water Cooling System	
Electronic Governor	

Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	291	406	528

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.
Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. $1 \text{ hp} = 1 \text{ kW} \times 1.36$

Engine Technical Data

No. of Cylinders / Alignment	18/60° V
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	170
Stroke, mm	190
Displacement, l	77.6
Compression Ratio	15.5:1
Starting	24V Electric
Alternators, Amps	24V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX322
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 150/40
Regulation	±0.5%
No. of Phases	3
No. of Poles	4

KMGC3000 GENSET

Generating Set Powered By



STAMFORD LEROY-SOMER™

Performances 1500rpm	
Alternator Efficiency	96.2%
Engine Power	
Prime Power, KWm(hp)	2269(3043)
Standby Power, KWm(hp)	2479(3324)
Alternator	
Prime Power, KW	2240

Lubrication System 1500rpm	
Oil Consumption (l/hr)	-
Oil Sump Capacity, l	413
Oil System Capacity Include Filters, l	466

Cooling System 1500rpm	
Heat Radiation from Engine and Alternator, Power KW	229
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	885
Radiator Cooling Air Flow, m³/s	-
Coolant Capacity (engine only), l	223.4

Intake & Exhaust System 1500rpm	
Air Flow Combustion at (Standby Power, m³/min(cfm)	193(6820)
Heat Rejection Exhaust at Standby Power, KW	1418
Exhaust Gas Temperature at Standby °C	427
Max Allowable Back Pressure in Exhaust Line, Kpa	6.8
Exhaust Gas Flow at Standby (Power, m³/min(cfm)	432.45(15272)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery Disconnect Switch
 - Electrical Governor
- **Alternator**
 - Excitation Boost System (EBS)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)

Genuine - Cummins

Oil filter	(4)
Fuel filter	(3)
Air filter	(4)
Fan belt set	(1)
Coolant filter	(2)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

