KHONAYSSER GROUP

KMGC-375 GENSET

Generating Set Powered By Cummins STAMFORD LEROY-SOMER

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz / 416-480V	266KWe/333KVA	300KWe/375KVA

Genset Specification

Engine Make & Model	**Cummins** QSL9-G5
Origin	India
Alternator Type	S4L1D-D41/TAL046F
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole MCCB
Water Cooling System	
Electronic Governor	

Fuel System (prime)	50%	75%	100%
1800rpm, 60Hz (L/hr)	36	55	75

International Standards

Engine confirm to ISO 9001: 2000, ISO 14001, ISO10054, ISO 3046,BS 5514,DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000,VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100,AS 1359, BS 6861 1, B En 61000-6-2:2001

ISO 9001 BUREAU VERITAS Certification — UKAS QUALITY MANAGEMENT

RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for govering purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	6/ In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	114
Stroke, mm	145
Displacement,l	8.8
Compression Ratio	16.8:1
Starting	24V Electric
Alternators, Amps	24V/70A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440 / R150
Protection	IP23
Temperature Rise,°C	Prime 125/40 Standby 163/27
Regulation	±1.0% - ±0.8%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	2.95	1.07	1.83	2300	300
Enclosed	4.53	1.47	2.20	3800	517

For the enclosed type:-
The sound level is around 85 dB(A) @ 3m .
The height to be increased by 12cm for the hook.

KHONAYSSER

@ 2023 Khonaysser Group - All Rights Reserved

KMGC-375 GENSET

Generating Set Powered By Cummins STAMFORD LEROY-SOMER™

Performances	1800rpm
Alternator Efficienc	92.9%
Engine Power	
Prime Power, KWm(hp)	293(392)
Standby Power, KWm(hp)	337(451)
Alternator	
Prime Power, KWe	275

Lubrication System	1800rpm
Oil Consumption (l/hr)	0.03
Oil Sump Capacity,l	22.7
Oil System Capacity Include Filters,l	26.5

Cooling System	1800rpm
Heat Radiation from Engine and Alternator, Power KW	40
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	140
Radiator Cooling Air Flow, m^3/s (cfm)	480(16951)
Coolant Capacity, l	47.7

Intake & Exhaust System	1800rpm
Air Flow Combustion at Standby Power, m^3/min(cfm)	24.6(870)
Heat Rejection Exhaust at Standby Power, KW	305
Exhaust Gas Temperature at Standby °C	580
Max Allowable Back Pressure in Exhaust Line, Kpa	10
Exhaust Gas Flow at Standby Power, m^3/min(cfm)	64.8(2300)

Accessories

Standard Silencer	**Anti-Vibration Pads**
Stainless Steel Flexible	**Genuine Coolant 'Ready Mix'**
Genuine Oil	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temparature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

• Engine
-Coolant heater
-Oversize batteries
-Extra fuel pre-filter water separator
-Battery Disconnector Switch
-Electrical Governor
• Alternator
-Excitation Boost System (EBS)
-Upgrade to 3 phase sensing AVR
-Qadrature droop kit
-Anti-condensation heater
-Air inlet filters
• General
-Upgrade to modular controller for paralleling
-Upgrade to 4 pole circuit breaker
-Battery charger
-Automatic transfer switch
-Fuel level switch High / Low for alarm and control
-Fuel transfer pump Automatic / Manual
-Residential grade silencer
-Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter	(1)
Fuel filter water separator	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(1)

General Information

Documentation
Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty
One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

KHONAYSSER

KHONAYSSER GROUP

Naher El Mott-Beirut-Lebanon Tel:+961 1 870078, Fax:+961 1 874795, P.O.Box:70268 **Doha-Qatar** Tel:+974 44503086 Fax:+974 44503786, 44161944 P.O.Box:11857
Riyadh-KSA Tel:+966 112252076, Fax:+966 112691402,P.O.Box:241241 **Dubai-UAE** Tel:+971 48811169, Fax:+971 48811164, P.O.Box:191902
Erbil - Iraq Tel: +964 750 30 12 907, Tel: +964 770 04 44 466, info@khonaysser.com, www.khonaysser.com