



KMGC275 GENSET

Generating Set Powered By



STAMFORD® LEROY-SOMER™

Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	200KWe / 250KVA	220KWe / 275KVA

Genset Specifications

Engine Make & Model	Cummins QSL9G3
Origin	India
Alternator Type	UCDI274K/TAL046D
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3 Pole MCCB
Water Cooling System	
Electronic Governor	
Emission Compliant	

Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	34	49	59

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS I359, BS 6861 1, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A 10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. $1 \text{ hp} = 1 \text{ kW} \times 1.36$

Engine Technical Data

No. of Cylinders / Alignment	6/ In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	114
Stroke, mm	145
Displacement, l	8.8
Compression Ratio	17.8:1
Starting	24V Electric
Alternators, Amps	24V/70A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R150
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	2.95	1.07	1.83	2050	300
Enclosed	3.97	1.28	2.00	3550	370

For the enclosed type:
The sound level is around 85 dB(A) @ 3m.
The height to be increased by 12cm for the hook.

KMGC275 GENSET

Generating Set Powered By 

STAMFORD LEROY-SOMER™

Performances	1500rpm
Alternator Efficiency	92.7%
Engine Power	
Prime Power, KW(hp)	217(291)
Standby Power, KW(hp)	244(327)
Alternator	
Prime Power, KWe	200

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR
- Oil pressure, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Lubrication System	1500rpm
Oil Consumption (l/hr)	0.03
Oil Sump Capacity, l	24
Oil System Capacity Include Filters, l	26.5

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
 - Battery Disconnector Switch
 - Electrical Governor
- **Alternator**
 - Excitation Boost System (EBS)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Intake & Exhaust System	1500rpm
Air Flow Combustion at Standby Power, m ³ /min(cfm)	18.9(660)
Heat Rejection Exhaust at Standby Power, KW	235
Exhaust Gas Temperature at Standby °C	585
Max Allowable Back Pres- sure in Exhaust Line, Kpa	10.2
Exhaust Gas Flow at Standby Power, m ³ /min(cfm)	51(1800)

Spare Parts Kit (Optional)

Genuine - Cummins

Oil filter	(l)
Fuel filter water separator	(l)
Fuel filter	(l)
Air filter	(l)
Fan belt set	(l)
Alternator belt set	(l)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

