



# KMGVP-760 GENSET

Generating Set Powered By **VOLVO PENTA** **STAMFORD** **LEROY-SOMER**™



Image for illustration purposes only

## Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz /416V	552KWe/690KVA	608KWe/760KVA

## Genset Specification

Engine Make & Model	Volvo Penta TWD1644GE -B
Origin	SWEDEN
Alternator Type	HCI544F/S5L1D-F41/TAL0473F
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole MCCB

## Tropical Cooling System

Fully Electronic with Volvo Penta EMS 2

## Emission Compliant

## CANBUS SAEJ1939 Interface

Fuel System	50%	75%	100%
1800rpm, 60Hz	73.9	108.2	144.2

## International Standards

Engine confirm to ISO 9001:2000,ISO 14001,ISO10054,ISO 3046,BS 5514,DIN 6271. Alternator confirm to ISO 9001,ISO 14001,BS EN 60034,BS 5000,VDE 0530,NEMA MG1-32,IEC34 CSA C22.2-100,AS I359,BS 6861 1,B En 61000-6-2:2001



## RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A 10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

## Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Electronic
Bore, mm	144
Stroke, mm	165
Displacement, l	16.12
Compression Ratio	16.8:1
Starting	24V Electric
Alternators, Amps	24V/80A

## Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R150
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 150/40
Regulation	±1.0% - ±0.8%
No. of Phases	3
No. of Poles	4

## Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	3.67	1.43	2.10	4644	500
Enclosed	5.23	1.76	2.50	6900	660

# KMGVP-760 GENSET

Generating Set Powered By **VOLVO PENTA**

**STAMFORD LEROY-SOMER™**

Performances	1800rpm
Alternator Efficiency	95.0%
<b>Engine Power</b>	
Prime Power, kW/hp	582(792)
Standby Power, kW/hp	640(870)
<b>Alternator</b>	
Prime Power, kWe	590

## Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load
- Oil pressure, water temperature, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Lubrication System	1800rpm
Oil Consumption (l/hr)	0.11
<b>Oil Sump Capacity, l</b>	42
Oil System Capacity Include Filters, l	48

## Optional Equipment

- **Engine**
  - Coolant heater
  - Oversize batteries
  - Extra fuel pre-filter water separator
  - Battery disconnector switch
- **Alternator**
  - Permanent magnet generator (PMG)
  - Upgrade to 3 phase sensing AVR
  - Quadrature droop kit
  - Anti-condensation heater
  - Air inlet filters
- **General**
  - Upgrade to modular controller for paralleling
  - Upgrade to 4 pole circuit breaker
  - Battery charger
  - Automatic transfer switch
  - Fuel level switch High / Low for alarm and control
  - Fuel transfer pump Automatic / Manual
  - Residential grade silencer
  - Weather protective and acoustic enclosure.

Intake & Exhaust System	1800rpm
Air Flow Combustion at Standby Power, m <sup>3</sup> /min(cfm)	46.7(1649)
<b>Heat Rejection Exhaust at Standby Power, KW</b>	495
Exhaust Gas Temperature at Standby °C	495
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>	10
Exhaust Gas Flow at Standby Power, m <sup>3</sup> /min(cfm)	114.5(4044)

## Spare Parts Kit (Optional)      Genuine - Volvo Penta

Oil filter, full flow	(2)
Oil filter, bypass	(1)
Fuel filter water separator	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(1)
Alternator belt set	(1)

## General Information

### Documentation

Engine instruction book-English  
Alternator manual- English  
Wiring diagram

### Warranty

One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

Accessories	
Oil Drain Pump	Standard Silencer
Stainless Steel Flexible	Anti-Vibration Pads
Genuine Oil (Volvo Penta)	Volvo Penta 'Ready Mix'

