



## KMGVP360 GENSET

Generating Set Powered By **VOLVO PENTA**

**STAMFORD LEROY-SOMER™**

Image for illustration purposes only

### Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz /400V	260KW <sub>e</sub> / 325KVA	288KW <sub>e</sub> / 360KVA

### Genset Specification

Engine Make & Model	Volvo Penta TAD843GE
Origin	India
Alternator Type	S4LID-E4I/TAL046H
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole MCCB

### Tropical Cooling System

Fully Electronic with Volvo Penta EMS2

### Emission Compliant

CANBUS SAEJ1939 Interface

Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	35.7	51.5	68

### International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.  
Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



### RATING GUIDELINES

**PRIME POWER** rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

**MAXIMUM STANDBY POWER** rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating.  $1 \text{ hp} = 1 \text{ kW} \times 1.36$

### Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Electronic
Bore, mm	110
Stroke, mm	135
Displacement, l	7.7
Compression Ratio	17.5:1
Starting	24V Electric
Alternators, Amps	24V/110A

### Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R150
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 150/40
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

### Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	2.99	1.15	1.55	2350	280
Enclosed	4.45	1.40	2.05	2700	320

# KMGVP360 GENSET

Generating Set Powered By **VOLVO PENTA** **STAMFORD LEROY-SOMER™**

Performances	1500rpm
<b>Alternator Efficiency</b>	93.5%
<b>Engine Power</b>	
Prime Power, KWm(hp)	292(397)
Standby Power, KWm(hp)	320(435)
<b>Alternator</b>	
Prime Power, KWe	280

Lubrication System	1500rpm
<b>Oil Consumption (l/hr)</b>	0.02
<b>Oil Sump Capacity, l</b>	25
<b>Oil System Capacity Include Filters, l</b>	27

Cooling System	1500rpm
<b>Heat Radiation from Engine and Alternator, Power KW</b>	-
<b>Heat Rejection to Coolant and Lube Oil at Standby Power, KW</b>	-
<b>Radiator Cooling Air Flow, m³/s</b>	6.2
<b>Coolant Capacity, l</b>	41

Intake & Exhaust System	1500rpm
<b>Air Flow Combustion at Standby Power, m³/min(cfm)</b>	19(671)
<b>Heat Rejection Exhaust at Standby Power, KW</b>	-
<b>Exhaust Gas Temperature at Standby °C</b>	455
<b>Max Allowable Back Pressure in Exhaust Line, Kpa</b>	10
<b>Exhaust Gas Flow at Standby Power, m³/min(cfm)</b>	-

Accessories	
<b>Oil Drain Pump</b>	<b>Standard Silencer</b>
<b>Stainless Steel Flexible</b>	<b>Anti-Vibration Pads</b>
<b>Genuine Oil (Volvo Penta)</b>	<b>Genuine Coolant 'Ready Mix'</b>

Control Panel Readings
<ul style="list-style-type: none"> <li>• AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.</li> <li>• Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load</li> <li>• Oil pressure, water temperature, low oil level, high oil temperature</li> <li>• DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure</li> <li>• Low coolant level - Configurable inputs&amp;outputs</li> <li>• Upgradable for GSM network connection, Signal SMS messages.</li> </ul>

Optional Equipment
<ul style="list-style-type: none"> <li>• <b>Engine</b> <ul style="list-style-type: none"> <li>-Coolant heater</li> <li>-Oversize batteries</li> <li>-Extra fuel pre-filter water separator</li> <li>-Battery disconnect switch</li> </ul> </li> <li>• <b>Alternator</b> <ul style="list-style-type: none"> <li>-Permanent magnet generator (PMG)</li> <li>-Upgrade to 3 phase sensing AVR</li> <li>-Qadrature droop kit</li> <li>-Anti-condensation heater</li> <li>-Air inlet filters</li> </ul> </li> <li>• <b>General</b> <ul style="list-style-type: none"> <li>-Upgrade to modular controller for paralleling</li> <li>-Upgrade to 4 pole circuit breaker</li> <li>-Battery charger</li> <li>-Automatic transfer switch</li> <li>-Fuel level switch High / Low for alarm and control</li> <li>-Fuel transfer pump Automatic / Manual</li> <li>-Residential grade silencer</li> <li>-Weather protective and acoustic enclosure.</li> </ul> </li> </ul>

Spare Parts Kit (Optional)	Genuine - Volvo Penta
Oil filter, full flow	(2)
Oil filter, bypass	(1)
Fuel filter water separator	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Coolant filter	(1)

General Information
<b>Documentation</b> Engine instruction book-English Alternator manual- English Wiring diagram

Warranty
One year with unlimited hours against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty

