



Image for illustration purposes only

KMGP1230 GENSET

Generating Set Powered By **PERKINS** **STAMFORD LEROY-SOMER™**

Output Ratings		
Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	900KWe/1125KVA	984KWe/1230KVA

Genset Specification			
Engine Make & Model	Perkins 4008-30TAG3		
Origin	UK		
Alternator Type	S6LID-F4I		
Control Panel	Deep Sea - 7310 MKII		
Circuit Breaker Type	3 Pole ACB		
Tropical Cooling System	Digital Electronic Governor		
Turbocharged	Exceptional Power to Weight Ratio		
Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	120	188	244

International Standards
 Engine conform to ISO 9001, 2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271.
 Alternator conform to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES
PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.
MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data	
No. of Cylinders / Alignment	8 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	160
Stroke, mm	190
Displacement, l	30.56 l
Compression Ratio	13.6:1
Starting	24V Electric
Alternators, Amps	24V/55A

Alternator Technical Data	
No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)					
	L	W	H	Weight	Tank Capacity(L)
Open	4.77	2.22	2.00	7450	N/A

KMGP1230 GENSET

Generating Set Powered By  Perkins 

Performances	1500rpm
Alternator Efficiency	95.5%
Engine Power	
Prime Power, KWm(hp)	947(1270)
Standby Power, KWm(hp)	1055(1408)
Alternator	
Prime Power, KWe	920

Lubrication System	1500rpm
Oil Consumption (g/kWhr)	0.4%
Oil Sump Capacity, l	153
Oil System Capacity Include Filters, l	-

Cooling System	1500rpm
Heat Radiation from Engine and Alternator, Power KW	74
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	331
Radiator Cooling Air Flow, m³/min (cfm)	1176(41530)
Coolant Capacity, l	140

Intake & Exhaust System	1500rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	96(3390)
Heat Rejection Exhaust at Standby Power, KW	896
Exhaust Gas Temperature at Standby °C	482
Max Allowable Back Pressure in Exhaust Line, Kpa	7.0
Exhaust Gas Flow at Standby Power, m³/min(cfm)	240(8475)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load
- Oil pressure, water temperature, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&output
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
- **Alternator**
 - 12wire reconnectable stator/terminal arrangement -
 - Quadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to ACB
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional) Genuine - Perkins

Oil filter , full flow	(3)
Fuel filter	(1)
Air filter	(2)
Fan belt set	(1)
Alternator belt set	(1)

General Information

Documentation
 Engine instruction book-English
 Alternator manual- English
 Wiring diagram

Warranty
 One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

