



Image for illustration purposes only

KMGVP220-1 GENSET

Generating Set Powered By

VOLVO PENTA STAMFORD LEROY-SOMER™

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz /400V	160KWe / 200KVA	176KWe / 220KVA

Genset Specification

Engine Make & Model	Volvo Penta TAD840GE-B
Origin	India
Alternator Type	UCI274H/TAL044M
Control Panel	Deep Sea - 6110 MKIII
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	
Fully Electronic with Volvo Penta EMS2	
Emission Compliant	
CANBUS SAEJ1939 Interface	
Fuel System (prime)	50% 75% 100%
1500rpm, 50 Hz (L/hr)	22.7 33.7 45.6

International Standards

Engine confirm to ISO 9001, 2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Electronic
Bore, mm	110
Stroke, mm	135
Displacement, l	7.7
Compression Ratio	17.5:1
Starting	24V Electric
Alternators, Amps	24V/110A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R120
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	± 1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	2.99	1.15	1.55	2250	280
Enclosed	4.45	1.40	2.05	2600	320

KMGVP220-1 GENSET

Generating Set Powered By **VOLVO PENTA STAMFORD LEROY-SOMER™**

Performances	1500rpm
Alternator Efficiency	93.3%
Engine Power	
Prime Power, KWm(hp)	177(241)
Standby Power, KWm(hp)	194(264)
Alternator	
Prime Power, KWe	160

Lubrication System	1500rpm
Oil Consumption (l/hr)	
Prime Power	0.02
Oil Sump Capacity, l	25
Oil System Capacity Include Filters, l	27

Cooling System	1500rpm
Heat Radiation from Engine and Alternator, Power KW (Standby)	7
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	90
Radiator Cooling Air Flow, m³/s	6.05
Coolant Capacity, l	41

Intake & Exhaust System	1500rpm
Air Flow Combustion at Standby Power, m³/min(cfm)	15.1(533)
Heat Rejection Exhaust at Standby Power, KW	157
Exhaust Gas Temperature at Standby °C	481
Max Allowable Back Pressure in Exhaust Line, Kpa	10
Exhaust Gas Flow at Standby Power, m³/min(cfm)	37(1307)

Accessories	
Oil Drain Pump	Standard Silencer
Stainless Steel Flexible	Anti-Vibration Pads
Genuine Oil (Volvo Penta)	Genuine Coolant 'Ready Mix'

Control Panel Readings
<ul style="list-style-type: none"> AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load Oil pressure, water temperature, low oil level, high oil temperature DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure Low coolant level - Configurable inputs&output Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator -Battery disconnect switch Alternator <ul style="list-style-type: none"> -Permanent magnet generator (PMG) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filter General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Volvo Penta
Oil filter, full flow	(1)
Fuel filter water separator	(1)
Fuel filter	(2)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information
Documentation
Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty
One year with unlimited hours against all defects in material / or workmanship, subject to the terms and conditions of the Manufacturer's warranty