



KMGC-125 GENSET

Generating Set Powered By 

STAMFORD **LEROY-SOMER**TM

Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1800rpm, 60Hz / 416V	92KWe/115kVA	100KWe/125KVA

Genset Specifications

Engine Make & Model	Cummins 6BTA5.9-G6
Origin	India
Alternator Type	UCI274D / TAL044D
Control Panel	Deep Sea - 6110 MKIII
Circuit Breaker Type	3Pole MCCB
Water Cooling System	
Electronic Governor	
Electrical Stop Solenoid, Energized to Run	
Compact Size	

Fuel System (prime)	50%	75%	100%
1800rpm, 60Hz (L/hr)	16	23	31

International Standards

Engine confirm to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	6/ In Line
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	102
Stroke, mm	120
Displacement, l	5.9
Compression Ratio	17.3:1
Starting	12V Electric
Alternators, Amps	12V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440 / R120
Protection	IP23
Temperature Rise, °C	Prime 125/40
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	2.64	0.85	1.62	1200	130
Enclosed	3.66	1.13	1.94	2150	195

For the enclosed type:-
The sound level is around 85 dB(A) @ 3m .
The height to be increased by 12cm for the hook.

KMGC-125 GENSET

Generating Set Powered By

STAMFORD **LEROY-SOMER**™

Performances 1800rpm	
Alternator Efficiency	90.5%
Engine Power	
Prime Power, KWm(hp)	112(150)
Standby Power, KWm(hp)	124(166)
Alternator	
Prime Power, KWe	105

Lubrication System 1800rpm	
Oil Consumption (l/hr)	0.08% of fuel consumption
Oil Sump Capacity, l	14.3
Oil System Capacity Include Filters, l	16.4

Cooling System 1800rpm	
Heat Radiation from Engine and Alternator, Power KW	14
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	76
Radiator Cooling Air Flow, m³/s	6.17
Coolant Capacity, l	19.75

Intake & Exhaust System 1800rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	10.5(370)
Heat Rejection Exhaust at Standby Power, KW	126
Exhaust Gas Temperature at Standby °C	551
Max Allowable Back Pressure in Exhaust Line, Kpa	10
Exhaust Gas Flow at Standby Power, m³/min(cfm)	28.2(995)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR Oil pressure, low oil level, high oil temperature DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure Low coolant level - Configurable inputs&outputs Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator -Battery Disconnect Switch -Electrical Governor Alternator <ul style="list-style-type: none"> -Excitation Boost System (EBS) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filters General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter	(1)
Fuel filter	(1)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information
<p>Documentation</p> <p>Engine instruction book-English Alternator manual- English Wiring diagram</p> <p>Warranty</p> <p>One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty</p>

