



KMGC2200 GENSET

Generating Set Powered By



STAMFORD LEROY-SOMER™

Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	1600KWe/2000kVA	1760KWe/2200kVA

Genset Specifications

Engine Make & Model	Cummins KTA50-G25
Origin	Inida
Alternator Type	S7LID-G4I
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3Pole ACB

Water Cooling System

Electronic Governor

Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	219.5	312.7	416.7

International Standards

Engine conform to ISO 9001:2000, ISO 14001, ISO 10054, ISO 3046, BS 5514, DIN 6271. Alternator conform to ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 1, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	16/60° V
Cycle	4 - Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	159
Stroke, mm	159
Displacement, l	50.3
Compression Ratio	14.7:1
Starting	24V Electric
Alternators, Amps	24V/55A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	PMG
Voltage Regulator	MX34I
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1%
No. of Phases	3
No. of Poles	4

KMGC2200 GENSET

Generating Set Powered By



STAMFORD LEROY-SOMER™

© 2023 Khonaysser Group - All Rights Reserved

Performances 1500rpm	
Alternator Efficiency	96.0%
Engine Power	
Prime Power, KWm(hp)	1683(2257)
Standby Power, KWm(hp)	1857(2491)
Alternator	
Prime Power, KWe	1664

Lubrication System 1500rpm	
Oil Consumption (l/hr)	-
Oil Sump Capacity, l	178
Oil System Capacity Include Filters, l	188

Cooling System 1500rpm	
Heat Radiation from Engine and Alternator, Power KW	186
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	574
Radiator Cooling Air Flow, m³/s	29
Coolant Capacity, l	438

Intake & Exhaust System 1500rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	140(4951)
Heat Rejection Exhaust at Standby Power, KW	1675
Exhaust Gas Temperature at Standby °C	543
Max Allowable Back Pressure in Exhaust Line, Kpa	6.8
Exhaust Gas Flow at Standby Power, m³/min(cfm)	348(12290)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings
<ul style="list-style-type: none"> AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor. Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR Oil pressure, low oil level, high oil temperature DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure Low coolant level - Configurable inputs&outputs Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment
<ul style="list-style-type: none"> Engine <ul style="list-style-type: none"> -Coolant heater -Oversize batteries -Extra fuel pre-filter water separator -Battery Disconnect Switch -Electrical Governor Alternator <ul style="list-style-type: none"> -Excitation Boost System (EBS) -Upgrade to 3 phase sensing AVR -Qadrature droop kit -Anti-condensation heater -Air inlet filters General <ul style="list-style-type: none"> -Upgrade to modular controller for paralleling -Upgrade to 4 pole circuit breaker -Battery charger -Automatic transfer switch -Fuel level switch High / Low for alarm and control -Fuel transfer pump Automatic / Manual -Residential grade silencer -Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Cummins
Oil filter	(4)
Fuel filter	(3)
Air filter	(4)
Fan belt set	(1)
Coolant filter	(2)

General Information
<p>Documentation</p> <p>Engine instruction book-English Alternator manual- English Wiring diagram</p> <p>Warranty</p> <p>One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty</p>

