KHONAYSSER GROUP



Image for illustration purposes only

KMGP-700 GENSET

Generating Set Powered By Perkins STAMFORD LEROY-SOMER™

Output Ratings

Speed,Frequency/Volt	Prime Power	Standby Power
1800rpm, 60 Hz / 416V	512KWe / 640KVA	560KWe/700KVA

Genset Specifications

Engine Make & Model	**Perkins** 2806A-E18TAG1A
Origin	USA
Alternator Type	S5L1D-E41/TAL0473E
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3 Pole MCCB
Tropical Cooling System	
Digital Electronic Governor	
Turbocharged	
Exceptional Power to Weight Ratio	

Fuel System (prime)	50%	75%	100%
1800rpm, 60Hz (L/hr)	66	95	127

International Standards

Engine confirm to ISO 9001: 2000, ISO 14001, ISO10054, ISO 3046,BS 5514,DIN 6271. Alternator confirm to ISO 9001, ISO 14001, BS EN 60034, BS 5000,VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100,AS 1359, BS 6861 1, B En 61000-6-2:2001

ISO 9001 BUREAU VERITAS Certification — UKAS

RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for govering purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. **1 hp = 1 kW x 1.36**

Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	145
Stroke, mm	183
Displacement,l	18.1
Compression Ratio	14.5:1
Starting	24V Electric
Alternators, Amps	24V/70A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R150
Protection	IP23
Temperature Rise,°C	Prime 125/40 Standby 150/40
Regulation	±1.0% - ±0.8%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	3.75	1.54	2.13	4400	400
Enclosed	4.98	1.76	2.97	6945	673

KHONAYSSER

© 2023 Khonaysser Group - All Rights Reserved

KMGP-700 GENSET

Generating Set Powered By Perkins STAMFORD LEROY-SOMER

Performances	1800rpm
Alternator Efficiency	94.8%
Engine Power Prime Power, KWm(hp) Standby Power, KWm(hp)	 543(728) 598(802)
Alternator Prime Power, KWe	 545

Lubrication System	1800rpm
Oil Consumption (l/hr)	0.1% of fuel consumption at full load
Oil Sump Capacity,l	53
Oil System Capacity Include Filters,l	62

Cooling System	1800rpm
Heat Radiation from Engine and Alternator, Power KW	44
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	190
Radiator Cooling Air Flow, m^3/min (cfm)	852(30087.5)
Coolant Capacity, l	61

Intake & Exhaust System	1800rpm
Air Flow Combustion at Standby Power, m^3/min(cfm)	45(1589)
Heat Rejection Exhaust at Standby Power, KW	482
Exhaust Gas Temperature at Standby °C	489
Max Allowable Back Pressure in Exhaust Line, Kpa	6.9
Exhaust Gas Flow at Standby Power, m^3/min(cfm)	118(4167)

Accessories

Standard Silencer	**Anti-Vibration Pads**
Stainless Steel Flexible	**Genuine Coolant 'Ready Mix'**
Genuine Oil	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temparature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load
- Oil pressure, water temparature, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

• Engine
-Coolant heater
-Oversize batteries
-Extra fuel pre-filter water separator
• Alternator
-Permanent magnet generator (PMG)
-Upgrade to 3 phase sensing AVR
-Qadrature droop kit
-Anti-condensation heater
-Air inlet filters
• General
-Upgrade to modular controller for paralleling
-Upgrade to 4 pole circuit breaker
-Battery charger
-Automatic transfer switch
-Fuel level switch High / Low for alarm and control
-Fuel transfer pump Automatic / Manual
-Residential grade silencer
-Weather protective and acoustic enclosure.

Spare Parts Kit (Optional)	Genuine - Perkins
Oil filter, full flow	(2)
Fuel filter	(1)
Fuel pre-filter water separator	(1)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information

Documentation
Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty
One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty.

KHONAYSSER

KHONAYSSER GROUP

Naher El Mott-Beirut-Lebanon Tel:+961 1 870078, Fax:+961 1 874795, P.O.Box:70268 **Doha-Qatar** Tel:+974 44503086 Fax:+974 44503786, 44161944 P.O.Box:11857
Riyadh-KSA Tel:+966 112252076, Fax:+966 112691402, P.O.Box:241241 **Dubai-UAE** Tel:+971 48811169, Fax:+971 48811164, P.O.Box:191902
Erbil - Iraq Tel: +964 750 30 12 907, Tel: +964 770 04 44 466, info@khonaysser.com, www.khonaysser.com