



KMGP500 GENSET

Generating Set Powered By Perkins



Image for illustration purposes only

STAMFORD LEROY-SOMER™

Output Ratings

Speed, Frequency/Volt	Prime Power	Standby Power
1500rpm, 50 Hz / 400V	360KWe / 450KVA	400KWe / 500KVA

Genset Specifications

Engine Make & Model	Perkins 2506A-E15TAG1
Origin	USA
Alternator Type	S4LI-G4I/TAL0473B
Control Panel	Deep Sea - 7310 MKII
Circuit Breaker Type	3 Pole MCCB

Tropical Cooling System

Digital Electronic Governor

Turbocharged

Exceptional Power to Weight Ratio

Fuel System (prime)	50%	75%	100%
1500rpm, 50 Hz (L/hr)	50	72	95

International Standards

□□□□□□□□□□□□□□

Alternator □□□□□ ISO 9001, ISO 14001, BS EN 60034, BS 5000, VDE 0530, NEMA MG1-32, IEC34 CSA C22.2-100, AS 1359, BS 6861 I, B En 61000-6-2:2001



RATING GUIDELINES

PRIME POWER rating corresponds to ISO Standard Power for continuous operation. It is applicable for supplying electrical power at variable load for an unlimited number of hours instead of commercially purchased power. A10 % overload capability for governing purpose is available for this rating.

MAXIMUM STANDBY POWER rating corresponds to ISO Standard Fuel Stop Power. It is applicable for supplying standby electrical power at variable load in areas with well established electrical networks in the event of normal utility power failure. No overload capability is available for this rating. 1 hp = 1 kW x 1.36

Engine Technical Data

No. of Cylinders / Alignment	6 In Line
Cycle	4 Stroke
Aspiration	Turbocharged
Injection	Direct
Bore, mm	137
Stroke, mm	171
Displacement, l	15.2
Compression Ratio	16:1
Starting	24V Electric
Alternators, Amps	24V/70A

Alternator Technical Data

No. of Bearings	Single Bearing
Insulation System	Class H
Excitation	Self Excited
Voltage Regulator	AS440/R150
Protection	IP23
Temperature Rise, °C	Prime 125/40 Standby 163/27
Regulation	±1.0%
No. of Phases	3
No. of Poles	4

Dimensions (m) & Weights (kg)

	L	W	H	Weight	Tank Capacity(L)
Open	3.70	1.24	1.99	3600	375
Enclosed	4.84	1.44	2.35	5375	554

KMGP500 GENSET

Generating Set Powered By  **Perkins**  **STAMFORD LEROY-SOMER™**

Performances 1500rpm	
Alternator Efficiency	93.3%
Engine Power	
Prime Power, KWm(hp)	396(531)
Standby Power, KWm(hp)	434(582)
Alternator	
Prime Power, KWe	360

Lubrication System 1500rpm	
Oil Consumption (l/hr)	0.1% of fuel consumption at full load
Oil Sump Capacity, l	53
Oil System Capacity Include Filters, l	62

Cooling System 1500rpm	
Heat Radiation from Engine and Alternator, Power KW	31.2
Heat Rejection to Coolant and Lube Oil at Standby Power, KW	147
Radiator Cooling Air Flow, m³/min (cfm)	722(25496)
Coolant Capacity, l	58

Intake & Exhaust System 1500rpm	
Air Flow Combustion at Standby Power, m³/min(cfm)	30.5(1077)
Heat Rejection Exhaust at Standby Power, KW	308
Exhaust Gas Temperature at Standby °C	550
Max Allowable Back Pressure in Exhaust Line, Kpa	6.8
Exhaust Gas Flow at Standby Power, m³/min(cfm)	81(2860)

Accessories	
Standard Silencer	Anti-Vibration Pads
Stainless Steel Flexible	Genuine Coolant 'Ready Mix'
Genuine Oil	

Control Panel Readings

- AC volts, AC currents, DC volts, frequency, rpm, hour counter, power factor.
- Low oil pressure, high water temperature, boost pressure and temperature, KW, KWh, KVA, KVAR, fuel consumption, relative load
- Oil pressure, water temperature, low oil level, high oil temperature
- DC alternator failure, over speed, over crank (Fail to start), over under voltage, over under current, any sensor failure
- Low coolant level - Configurable inputs&outputs
- Upgradable for GSM network connection, Signal SMS messages.

Optional Equipment

- **Engine**
 - Coolant heater
 - Oversize batteries
 - Extra fuel pre-filter water separator
- **Alternator**
 - Permanent magnet generator (PMG)
 - Upgrade to 3 phase sensing AVR
 - Qadrature droop kit
 - Anti-condensation heater
 - Air inlet filters
- **General**
 - Upgrade to modular controller for paralleling
 - Upgrade to 4 pole circuit breaker
 - Battery charger
 - Automatic transfer switch
 - Fuel level switch High / Low for alarm and control
 - Fuel transfer pump Automatic / Manual
 - Residential grade silencer
 - Weather protective and acoustic enclosure.

Spare Parts Kit (Optional) Genuine - Perkins

Oil filter, full flow	(2)
Fuel filter	(1)
Fuel pre-filter water separator	(1)
Air filter	(1)
Fan belt set	(1)
Alternator belt set	(1)

General Information

Documentation

Engine instruction book-English
Alternator manual- English
Wiring diagram

Warranty

One year with unlimited hours against all defects in material or workmanship, subject to the terms and conditions of the Manufacturer's warranty

